

5HZ6

Sharp-Cutoff Pentode With Two Independent Control Grids

Controlled Heater Warm-up Time

The 5HZ6 is the same as the 6HZ6 except for:

Heater Characteristics and Ratings

| | | |
|---|-------------------|---|
| Current | 0.600 \pm 0.040 | A |
| Voltage (ac or dc) at 0.600 A | 4.75 | V |

5J6

Medium-Mu Twin Triode

Controlled Heater Warm-up Time

The 5J6 is the same as the 6J6A except for:

Heater Characteristics and Ratings

| | | |
|---|-------------------|---|
| Current | 0.600 \pm 0.040 | A |
| Voltage (ac or dc) at 0.600 A | 4.7 | V |

5KE8

Medium-Mu Triode— Sharp-Cutoff Pentode

The 5KE8 is the same as the 6KE8 except for:

Heater Characteristics and Ratings

| | | |
|---|-------------------|---|
| Current | 0.450 \pm 0.030 | A |
| Voltage (ac or dc) at 0.450 A | 5.6 | V |
| Warm-up Time (Average) | 11 | s |

5MQ8

Medium-Mu Triode— Sharp-Cutoff Pentode

The 5MQ8 is the same as the 6MQ8 except for:

Heater Characteristics and Ratings

| | | |
|---|-------------------|---|
| Current | 0.600 \pm 0.040 | A |
| Voltage (ac or dc) at 0.600 A | 5.6 | V |
| Warm-up Time (Average) | 11 | s |